



# ANATECH MICROWAVE COMPANY

## Manufacturer & Supplier of RF & MW Filters



### 3475MHz WiMAX BANDPASS FILTER

P/N: AM 3475B552

#### SPECIFICATION:

Center frequency(Fo)	3475MHz
Pole	3
Bandwidth(BW)	50 MHz
Insertion Loss(Fo)	2.0 dB max
VSWR in BW	1.7 max
Ripple in BW	1.0 dB max
Attenuation	Fo +75MHz at 8dB min Fo +200MHz at 25dB min Fo -200MHz at 25dB min
In/Out Impedance	50 ohm

#### DIMENSION:

